

Table 4 : Content, order and format of the product data sheet

| | Parameter | Parameter value and precision | | | Unit |
|-----|--|---|---|------|-----------------|
| 1. | Supplier's name or trade name | Işı k Elektronik San.ve Tic. A.Ş | | | |
| | Supplier's address | Osmangazi Mah. Ahmet Yesevi Cad.No:12 Esenyurt / İstanbul | | | |
| 2. | Model identifier | ML55EW8000F | | | |
| 3. | Energy efficiency class for Standard Dynamic Range (SDR) | E | | | |
| 4. | Operating power demand for Standard Dynamic Range (SDR) | 63,0 | | | W |
| 5. | Energy efficiency class for High Dynamic Range (HDR) | E | | | |
| 6. | Operating power demand for High Dynamic Range (HDR) | 64,0 | | | W |
| 7. | Off-position power demand | 0 | | | W |
| 8. | Hibernation power demand | 0,5 | | | W |
| 9. | Networked hibernation power demand | 0 | | | W |
| 10. | Electronic display type | Television/ Monitor | | | |
| 11. | Aspect ratio | 16 | : | 9 | integer |
| 12. | Screen resolution (pixels) | 3840 | x | 2160 | Pixels |
| 13. | Screen diagonal | 139 | | | Cm |
| 14. | Screen diagonal | 55 | | | İnches |
| 15. | Visible screen area | 82,3 | | | dm ² |
| 16. | Used panel technology | ULTRA HD LED | | | |
| 17. | Available Automatic Brightness Control (ABC) | No | | | |
| 18. | Available voice recognition sensor | No | | | |
| 19. | Motion sensor available | No | | | |
| 20. | Image refresh frequency rate (default) | 60 | | | Hz |
| 21. | Minimum guaranteed availability of software and firmware updates (from the end of market sale) | 8 | | | years |
| 22. | Minimum guaranteed availability of spare parts (from the end of market sale) | 7 | | | years |
| 23. | Minimum warranty product support | 2 | | | years |
| | Minimum duration of the general warranty offered by the supplier | 2 | | | years |
| 24. | Power supply type | Internal | | | |
| 25. | External power supply (non-standardized and included in the product box) | | | | |
| | i, ii, iii | Standard Name | - | | |
| | | Input Voltage | - | | V |
| | | Output Voltage | - | | V |
| 26. | Standardized external power supply (or appropriate one if not included in the product box) | Standard Name | - | | |
| | | Required output voltage value | - | | V |
| | | Required passing current value (minimum) | - | | A |
| | | Required current frequency | - | | Hz |

* bb, yy, zz codes are variables such as model name, cabin type, control type, color given according to customer demand. Codes can be a number 0-9 or a space or a symbol.